



The *Energizer*® VISION HD Performance light with Digital Focus features MAXVIZ technology that offers outstanding beam natural color and optimized contrast, giving users an expanded field of high-definition vision. *Energizer*® proprietary Digital Focus Technology enables users to have optimum control of their light for enhanced direct and peripheral vision. The exceptional user control with enhanced light output makes this light ideal for the home, vehicle or workplace. Experience *Energizer*® Vision HD Performance Light with Digital Focus for the ultimate lighting control in the palm of your hand.

Lumens	Runtime	Beam Distance	Drop	Water Ingress
FL1 STANDARD 400 LUMENS	FL1 STANDARD 4h	FL1 STANDARD 115m	FL1 STANDARD 1m	FL1 STANDARD IPX4



BATTERY SPECIFICATIONS			
Battery Type	Energizer Max Alkaline		
Battery Size	AA		
Number of Cells	2		
BATTERY PERFORMANCE			
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)
High	400	4	115
Low	50	21	35
Strobe	-	-	-
Spot High	Digital Focus		
Spot Low			
Wide High			
Wide Low			
Modes			
High, Low, Strobe, Spot High, Spot Low, Wide High, Wide Low			

DESIGN BENEFITS	
✓ Durable aircraft grade aluminum construction ✓ One press digital focusing allows consumers to adjust light beam between focus and area light ✓ 20 Year Design To Last based on typical consumer usage patterns	
PERFORMANCE BENEFITS	
✓ MAXVIZ Technology to deliver a wide, powerful beam and high-definition vision ✓ Up to 15X brighter than standard LED technology ✓ Extended run time ✓ Shatterproof lens	
LIGHT AND POWER SOURCE	
✓ Features LED Technology ✓ 4.25hz strobe light ✓ Operates on 2 AA for maximum brightness runtime	
PRODUCT SPECIFICATIONS	
Weight:	108 Grams / 3.81 Ounces
Dimensions:	159 mm x 30 mm x 22 mm 6.25" x 1.19" x 0.88"
ELECTRICAL CHARACTERISTICS	
Nominal Power Consumption:	3.3 W
Batteries:	2 AA Energizer E91 3.0V dc
LED Specifications:	LED 3.0V cc / 1100 mA
DISCLAIMERS	
Tested according to ANSI FL1 Standards. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.	
CERTIFICATES AND COMPLIANCE	
EMC, EN62471, FCC CE RoHS UK CA	

OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1X for High.
3. Press 2X for Low.
4. Press 3X for Strobe.

BATTERY CHANGING INSTRUCTIONS

1. Batteries (2X AA) are user replaceable.
2. Insert batteries according to instruction printed on flashlight.